

VI-UTP-3105

PoE switch with uplink via UTP

- IP/PoE Extender Switch for UTP
- Distances up to 500m
- PoE and PoE+ and PoE++
- 4-Port Switch



With the VI-UTP-3105 switch, four 10/100BaseTX Ethernet ports can be uplinked via UTP cable using one uplink. The switch has been specially designed for use in existing installations. The VI-UTP-3105 allows existing UTP cabling to be used with Cat5e or better or generally with twisted pairs for Video over IP or generally for IP. No software configuration is required thanks to time-saving "plug-and-play". The small size and wide operating temperature range make the VI-UTP-3105 very versatile.

Video network special features

test fett



Technical data

General properties

| | |
|-----------------------|--|
| supply voltage | If sufficient power is supplied with PoE+ or PoE++ over the extender line, no local power supply is required. If the line losses on the extender line are too high, the VI-UTP-3105 can be supplied locally: 56VDC to 120W, e.g. VI-1120. Power requirement without PoE: 12VDC, 2A |
| MTBF | |
| operating temperature | -30 to +75°C |
| dimensions | 126 x 95 x 30mm |
| weight | 0,1kg |

interfaces

| | |
|-----------------------|---|
| copper ports | 4 x 10/100BaseT, PoE, PoE+, PoE++, RJ45 |
| extender ports | 1 x RJ45 |
| transmission cable | Ideal type: Cat5e and better Further types: When using Cat3 cables (telephone cable) or bell wire, the possible distances are significantly reduced. If Cat7 cables are used, the same distances can be expected as for Cat5e/Cat6. The shielding of the Cat7 cable must not be earthed. |
| Transmission distance | Die maximale Übertragungsdistanz bei Verwendung von Cat5e-Kabel oder besser beträgt ca. 500m Bei der Übertragung von PoE muss die Verlustleistung der Übertragungsstrecke berücksichtigt werden. |

Product variants

VI-UTP-3105

PoE-Switch mit Uplink über UTP



Version 17.09.2018, Changes without notice